

# Xerox® WorkCentre® 3615

## Black and White Multifunction Printer



WorkCentre 3615DN	
<b>Output Speed</b>	Up to 47 ppm 8.5 x 11 in. Up to 45 ppm A4 / 210 x 297 mm Up to 38 ppm 8.5 x 14 in. / 216 x 356 mm
<b>Automatic Two-sided</b>	Up to 29 ppm 8.5 x 11 in. Up to 28 ppm A4 / 210 x 297 mm Up to 25 ppm 8.5 x 14 in. / 216 x 356 mm
Paper Handling – Input	
Duplex Automatic Document Feeder (DADF)	
<b>Capacity<sup>1</sup></b>	60 sheets
<b>Sizes</b>	5.5 x 5.5 in. to 8.5 x 14 in. / 140 x 140 mm to 216 x 356 mm
<b>Weights</b>	Simplex: 13 to 32 lb. bond / 50 to 125 gsm Duplex: 13 to 32 lb. bond / 50 to 125 gsm
Multipurpose Tray	
<b>Capacity<sup>1</sup></b>	150 sheets
<b>Sizes</b>	Custom sizes: 3 x 5 in. to 8.5 x 14 in. / 76 x 127 mm to 216 x 356 mm
<b>Weights</b>	16 lb. bond to 80 lb. cover / 60 to 216 gsm
<b>Media Types</b>	Plain Plain thick Other Card stock Lightweight Heavyweight Rough surface Labels Envelopes Letterhead Hole punched
Tray 1	
<b>Capacity<sup>1</sup></b>	550 sheets
<b>Sizes</b>	Custom sizes: 5.8 x 8.3 in. to 8.5 x 14 in. / 148 x 210 mm to 216 x 356 mm
<b>Weights</b>	16 lb. bond to 80 lb. cover / 60 to 216 gsm
<b>Media Types</b>	Plain Plain thick Other Card stock Lightweight Heavyweight Rough surface Labels Letterhead Hole punched
Up to 3 Additional Trays (Optional)	
<b>Capacity<sup>1</sup></b>	550 sheets each
<b>Sizes</b>	Custom sizes: 5.8 x 8.3 in. to 8.5 x 14 in. / 148 x 210 mm to 216 x 356 mm
<b>Weights</b>	16 lb. bond to 80 lb. cover / 60 to 216 gsm

<b>Media Types</b>	Plain Plain thick Other Card stock Lightweight Heavyweight Rough surface Labels Letterhead Hole punched
<b>Paper Input Capacity</b>	
<b>Standard Paper Capacity<sup>1</sup></b>	700 sheets
<b>Maximum Paper Capacity<sup>1</sup></b>	2,350 sheets
<b>Paper Output</b>	
<b>Automatic Two-sided Output</b>	250 sheets
<b>Print</b>	
<b>First-page-out Time</b>	As fast as 6.5 seconds
<b>Print Resolution</b>	Up to 1200 x 1200 dpi
<b>Maximum Print Area</b>	4 mm from all edges or 207.7 mm x 347.4 mm (default), 215.9 mm x 255.6 mm with edge-to-edge mode
<b>Memory (std / max)</b>	1 GB / 1 GB
<b>Processor</b>	525 MHz
<b>Page Description Languages</b>	PCL® 5e and 6 emulations PostScript® 3™ emulation PDF emulation
<b>Connectivity</b>	10/100/1000Base-T Ethernet High Speed USB 2.0 USB Direct Print Optional Wi-Fi (with Xerox® Wireless Networking Adapter)
<b>Print Features</b>	Booklet printing Scaling Fit to page Watermarks Custom-size pages N-up Toner save mode Secure print Collation Print from USB memory device
<b>Supported Operating Systems</b>	Microsoft® Windows® XP SP1, Vista, 7, 2008 Server, 2003 Server Mac OS® 10.5 and later Various Linux® and UNIX® distributions, including: <ul style="list-style-type: none"> <li>• IBM® AIX® 5</li> <li>• HP-UX® 11i v2</li> <li>• openSUSE® 11</li> <li>• Red Hat® Fedora® Core 11-14</li> <li>• Ubuntu®</li> </ul>
<b>Print Drivers</b>	Microsoft Windows XP and above 2003 Server and above Mac OS 10.5 and above Red Hat Enterprise 4, 5 Fedora Core 14-16 openSUSE 11, 12 IBM AIX-5 HP-UX 11, 11i Solaris® 9, 10 Ubuntu Xerox® Global Print Driver® Xerox® Mobile Express Driver®
<b>Font Capability</b>	87 PostScript® Fonts; 88 PCL® Fonts
<b>Xerox® Mobile Express Driver®</b>	Makes it easy for mobile users to find, use and manage Xerox® and non-Xerox devices in every new location. Plug into a new network, and Xerox® Mobile Express Driver automatically discovers available printers and provides status and capability information. Save a list of "favourite" printers for each location, store application print settings for use on any printer in any network, and greatly reduce mobile support calls to IT. <ul style="list-style-type: none"> <li>• Printers are automatically discovered</li> <li>• Printer list can be managed based on location</li> <li>• Gives Bidirectional feedback device status, supplies, queue management</li> </ul>

<b>Xerox® Global Print Driver®</b>	A truly universal print driver that lets IT administrators install, upgrade and manage Xerox® and non-Xerox devices from a single driver. It provides a consistent, easy-to-use interface for end-users, reducing the number of support calls, and simplifying print services management. <ul style="list-style-type: none"> <li>• Printers are automatically discovered</li> <li>• Printer list can be managed based on location</li> <li>• Gives Bidirectional feedback device status, supplies, queue management</li> </ul>
<b>Copy</b>	
<b>Copy Speed</b>	Up to 42 copies per minute (cpm) 8.5 x 11 in. / 40 cpm A4
<b>Document Scanner</b>	Duplex Automatic Document Feeder with 60-sheet capacity
<b>Document Scanner Size</b>	Platen: Up to 8.5 x 14 in. / 216 x 356 mm DADF: Up to 8.5 x 14 in. / 216 x 356 mm
<b>Sides (input:output)</b>	1:1, 1:2, 2:2 and 2:1
<b>Quantity</b>	1 to 999
<b>Resolution</b>	Up to 600 x 600 dpi
<b>First-copy-out Time</b>	As fast as 8.5 seconds
<b>Copy Features</b>	Automatic background suppression Darkness control ID card copy Edge erase N-up Job build Photo build Photo mode Programme ahead
<b>Fax</b>	
<b>Fax Speed</b>	33.6 Kbps
<b>Memory</b>	4 MB
<b>Resolution</b>	Up to 400 x 400 dpi (Super Fine) resolution Up to 300 x 300 dpi (Photo) resolution Up to 203 x 196 dpi (Fine) resolution Up to 203 x 98 dpi (Standard) resolution
<b>Compression</b>	MH, MR, MMR, JBIG
<b>Fax Features<sup>2</sup></b>	Reject Junk Fax Distinctive Ring Pattern Detection Fax Forwarding to Fax, Email and Server with / without Local Print Polling Receive Delayed Start (up to 24 hours) Broadcast Sending (up to 200 destinations) Fax Address Book (up to 200 speed dial) Secure Fax Receive
<b>LAN Fax Features</b>	Delayed Start (up to 24 hours) Broadcast Sending (up to 30 destinations) Zoom Auto Fit Rotation N-up Watermark Phonebook (up to 500 speed dial numbers, up to 500 group dial, Phonebook stored on PC)
<b>Scan</b>	
<b>Capability</b>	Black and white and colour scanning
<b>Input Speed</b>	Up to 40 images per minute (ipm)
<b>Resolution (max)</b>	Up to 1200 x 1200 dpi
<b>Bit Depth</b>	8-bit grayscale, 24-bit colour
<b>Maximum Scan Area</b>	8.5 x 11 in. / 215.9 x 355.6 mm
<b>Network Filing Protocol</b>	FTP, SMB
<b>File Formats</b>	JPEG TIFF Multipage TIFF PDF
<b>Scan Driver Compatibility</b>	WIA, TWAIN
<b>Supported Scan Destinations</b>	Scan to computer via SMB Scan to server via FTP Scan to email with LDAP support Scan to USB memory device Scan to Network Address Book (up to 32 destinations) WSD scanning

Scanning Solutions			
<b>Xerox® Scan to PC Desktop® SE Small Business Edition (1-seat license)</b>	<p>A desktop and server-based offering that provides document imaging, archiving, editing and organisation tools</p> <ul style="list-style-type: none"> <li>• Nuance PaperPort – image viewing and file management software</li> <li>• Nuance OmniPage (for desktop / client installation) – OCR and file format conversion software</li> <li>• Image Retriever – provides fully automated retrieval of scanned images direct from a scan enabled Xerox® WorkCentre to individual desktops.</li> </ul> <p>For more information, visit <a href="http://www.xerox.com/scan2pcSE">www.xerox.com/scan2pcSE</a>.</p>		
Security			
<b>Security Features</b>	Secure HTTPS (SSL, Secure LDAP) IPsec 802.1X Authentication Network Authentication IPv6 SNMPv3 IP Filtering Secure Print Secure Fax Receive		
Wi-Fi Security			
	<b>Authentication Method</b>	<b>Encryption</b>	<b>Productivity Kit</b>
	Open WPA PSK WPA PSK / WPA2 PSK	WEP 64 / 128 ASCII / HEX TKIP AES	No
	WPA Enterprise WPA Enterprise / WPA 2™ Enterprise WPA Enterprise Authentication Method options: <ul style="list-style-type: none"> <li>• PEAPVO MS-CHAPV2</li> <li>• EAP-TLS</li> <li>• EAP-TTLS PAP</li> <li>• EAP-TTLS CHAP</li> </ul>	TKIP AES	Yes
Device Management			
Xerox® CentreWare® Web			
	<ul style="list-style-type: none"> <li>• A Web-based server application for network administrators that permits web browser-based device management from any workstation, whether running Windows or UNIX or any other operating system</li> <li>• Works with any SNMP-managed printer from any manufacturer</li> <li>• Provides help with device discovery and installations, health checks and troubleshooting, and device upgrades, as well as basic accounting and asset management</li> </ul>		
Xerox® CentreWare® Internet Services – Integrated Device Web Page			
<b>Device Status</b>	Web server embedded <ul style="list-style-type: none"> <li>• Tray status / contents</li> <li>• Consumables status</li> </ul>		
<b>Print Queue Viewing</b>	Complete job print queue management – hold, release, promote and delete		
<b>Job Submission</b>	Print-ready files (PS, PCL®, TIFF, PDF) Output feature selection		
<b>Device Administration</b>	Allows simple, remote installation setting of configuration options and management of the device		
<b>Browsers</b>	Microsoft® Internet Explorer® 7 Firefox® version 4 and above		
Xerox® Mobile Solutions and Apps			
<b>Xerox® Mobile Express Driver®</b>	The Xerox® Mobile Express Driver is a single, universal printer driver that can be downloaded to a PC and used to print to virtually any PostScript device on the network, including printers made by other manufacturers. Instead of downloading individual printer drivers for each product in each office, users can download the single, simple, Mobile Express Driver.		
<b>Apple® AirPrint™</b>	Print email, photos and important office documents directly from an Apple iPhone® or iPad® with no drivers to install and no cables to connect. With AirPrint, an iPhone or iPad automatically locates and connects to the AirPrint-enabled device over the office Wi-Fi network.		
<b>Google Cloud Print™</b>	Google Cloud Print connects print devices to the web, enabling users to print the applications they use every day from smartphones, tablets, Chromebook™ notebook computers and any other web-connected device.		
<b>Xerox® Print Service Plug-in for Android™</b> (Free at Google Play™ Store)	The Xerox® Print Service Plug-in for Android KitKat (4.4 or greater) devices streamlines mobile printing without third-party apps or additional print drivers. You can easily print photos, Web pages and documents when your mobile device is connected to ConnectKey-enabled multifunction printers using a wireless network. A robust print option set includes two-sided printing, stapling and secure code release. A free download is available from the Google Play™ store.		

<b>Xerox® Wireless Print Solutions Adapter</b> (Optional)		<p>The Xerox® Wireless Print Solutions Adapter seamlessly connects your Xerox® printer or multifunction printer to modern mobile and desktop workflows, regardless of your office environment. The Xerox® Wireless Print Solutions Adapter is your choice when:</p> <ul style="list-style-type: none"> <li>• Your printer or multifunction printer is not connected to a network but you want the ability to print from mobile devices.</li> <li>• You need to bridge Wi-Fi connectivity with a traditional hardware network.</li> <li>• You want Google Cloud Print™ 2.0 (print device requires Adobe® PostScript® compatibility) or Mopria® capabilities.</li> <li>• You want NFC tap-to-pair capabilities (requires the Xerox® Print Service Plug-in for Android).</li> <li>• You own a Xerox® printer or multifunction printer without embedded Apple® AirPrint™ support and want to add AirPrint compatibility (requires PostScript compatibility. The Xerox® Wireless Print Solutions Adapter's AirPrint functionality works with all Xerox® printers and multifunction printers that natively support AirPrint, and enables AirPrint on older Xerox® devices listed below that do not natively support AirPrint.)</li> <li>• You want Wi-Fi Direct, which lets you connect your computer or mobile device to your printer or multifunction printer wirelessly without the need for an access point or existing Wi-Fi network.</li> <li>• You need performance that comes from the cutting-edge Wi-Fi 802.11ac standard, which ensures data transfer that's almost twice as fast as existing 802.11n devices.</li> <li>• You need 256-bit encryption and advanced wireless security protocols, including WPA2™ Enterprise, HTTPS, and industry-standard 802.1X authentication.</li> </ul> <p>For more information, visit <a href="http://www.xerox.com/WPSA">www.xerox.com/WPSA</a>.</p>			
<b>Device Specifications</b>					
<b>Duty Cycle</b>					
	Up to 110,000 pages per month <sup>3</sup>				
<b>Recommended Monthly Print Volume</b>					
	Up to 12,000 pages per month <sup>4</sup>				
<b>Power Consumption</b>					
<b>110 to 127 VAC, 50 / 60 Hz, 11A or 220 to 240 VAC, 50 / 60 Hz, 6A</b>					
<b>Continuous Printing</b>	698 W				
<b>Ready (Standby) Mode</b>	59 W				
<b>Energy Saver Mode (Sleep)</b>	4 W				
<b>Environment</b>					
<b>Warm-up Time</b>	UI ready: <20 seconds First page printed: <20 seconds				
<b>Temperature Range</b>	59° to 82° F / 15° to 28° C				
<b>Humidity</b>	20 to 70%				
<b>Sound Pressure Levels</b>					
<b>Printing / Copying</b>	56 dB(A)				
<b>Standby</b>	30 dB(A)				
<b>Energy Save Mode</b>	0 dB(A)				
<b>Sound Power Levels</b>					
<b>Printing / Copying</b>	7.48 B(A)				
<b>Standby</b>	5.3 B(A)				
<b>Dimensions and Weights (Unpackaged)</b>		<b>Width</b>	<b>Depth</b>	<b>Height</b>	<b>Weight</b>
<b>WorkCentre 3615DN</b>	19.5 in. / 495 mm	19.4 in. / 492 mm	21.7 in. / 549 mm	47.4 lb. / 21.5 kg	
<b>550-sheet Feeder</b>	17 in. / 432 mm	18.3 in. / 465 mm	3.7 in. / 94 mm	7.7 lb. / 3.5 kg	
<b>Stand</b>	17.4 in. / 442 mm	18.5 in. / 470 mm	15.4 in. / 390 mm	29 lb. / 13.3 kg	
<b>Dimensions and Weights (Packaged)</b>					
<b>WorkCentre 3615DN</b>	24.6 in. / 626 mm	19.4 in. / 618 mm	27.7 in. / 703 mm	58.6 lb. / 26.6 kg	
<b>550-sheet Feeder</b>	21.1 in. / 535 mm	29.7 in. / 754 mm	9.2 in. / 234 mm	11.5 lb. / 5.0 kg	
<b>Stand</b>	20.3 in. / 515 mm	20.1 in. / 510 mm	9.1 in. / 230 mm	33 lb. / 15.4 kg	
<b>Certifications</b>					
	<p>UL 60950-1:2007 / CSA 60950-1-07+A1:2011, FDA / CDRH – Class 1 Laser Product, FCC Part 15, Class A, Canada ICES-003, Class A, CE marked, Low Voltage Directive 2006 / 95 / EC, EN 60950-1, 1st Edition, EN 60825-1 – Class 1 Laser Product, EMC Directive 2004 / 108 / EC, EN 55022, Class B, RoHS Directive 2011 / 65 / EU, WEEE Directive 2002 / 96 / EC, ENERGY STAR® qualified, Citrix Ready®, Blue Angel</p> <p>To view the latest list of certifications, go to <a href="http://www.xerox.com/OfficeCertifications">www.xerox.com/OfficeCertifications</a>.</p>				
<b>What Comes in the Box</b>					
	<p>WorkCentre 3615 Multifunction Printer            Toner cartridge (5,900 page capacity<sup>5</sup>)            Drum cartridge (68,000 page capacity<sup>6</sup>)            Quick Installation Guide, Quick Use Guide, Driver CD, Documentation CD (User Manual, System Admin. Guide)            Power cable            Fax cord</p>				

# Xerox® WorkCentre® 3615

Supplies and Options	Description	Order Number
<b>Standard Capacity Toner Cartridge</b>	5,900 impressions <sup>5</sup>	106R02721
<b>High-Capacity Toner Cartridge</b>	14,100 impressions <sup>5</sup>	106R02723
<b>Extra-high Capacity Toner Cartridge</b>	25,300 impressions <sup>5</sup>	106R02732
<b>Drum Cartridge</b>	68,000 impressions	113R00773
Options	Description	Order Number
<b>550-sheet Feeder</b>	Adjustable up to A4 / legal	497K13630
<b>Productivity Kit</b>	Includes 4 GB device memory, expanded Secure Print, Saved Print, expanded Job Collation, Security Certificates Storage, Font / Form / Macro Storage	497K13650
<b>Stand</b>	Adds storage capacity for supplies, device stability, mobility and 15.4 in. of height	497K13660
<b>Wireless Networking Adapter</b>	Expand workflow options for your Xerox® equipment	097S04409

<sup>1</sup> Paper capacities are based on 20 lb / 75 gsm stock. Capacities will vary with different weight stocks.

<sup>2</sup> Analog phone line required.

<sup>3</sup> Maximum volume capacity expected in any one month. Not expected to be sustained on a regular basis.

<sup>4</sup> Range reflects the number of pages per month the product can regularly print while maintaining optimal performance (considering factors including supplies replenishment and reliability over the expected product life).

<sup>5</sup> Average standard pages. Declared Yield in accordance with ISO/IEC 19752. Yield will vary based on image, area coverage and print mode.

<sup>6</sup> Approximate pages. Declared Yield Drums based on an average job size of 3 pages A4/letter size. Drum yield will vary based on job run length, media type, size, weight, orientation and usage patterns.

